

### DRM1X Connections:

Remove modules from enclosures and take off any existing power cables.

First place the DRM1 & DRM1X face down and side-by-side as shown.

Remove the three jumpers [red or blue] from the DRM1.  
Connect in the following order.

2pin Cables:

- SectCVs/OFCV  
11.5cm pink/purple
- AmpCVs/AMPS  
14.5cm white/grey

3pin Cables:

- SYNC – 13.5cm  
Yellow/Orange/Brown
- HP/LP/FILT – 10cm  
Pink/Purple/White
- F-Trig/FTRG – 15cm  
White/Grey/Brown

4pin Cables:

- Misc – 19cm  
White/Grey/Black/Purple
- Envs – 14cm  
Yellow/Orange/Brown/Grey

Each module then needs a regular 4pin Power Cable.

